

# 3000 WATTS GP SERIES Portable Inverter Generator

**GENERAC**<sup>®</sup>



GP3000i Portable Inverter Generator featuring PowerRush™ Advanced Technology

# GP3000i

## PORTABLE INVERTER GENERATOR

### Light and quiet power on the go.

Power whenever and wherever you need it, the Generac GP3000i inverter featuring new, advanced PowerRush™ technology delivers over 50 percent more starting capacity for your RV essentials and other motor-driven equipment—so you can do more with less.\* Quiet inverter power—perfect for outdoor activities in a compact and lightweight solution.

**OVER 50% MORE STARTING CAPACITY**  
with new, advanced PowerRush™ technology so you can do more with less\*

**QUIET INVERTER POWER**  
that reduces sound emissions and provides optimal performance



**EASY-TO-CARRY**  
with a compact and lightweight built-in handle

**ONE SIMPLE-TO-USE DIAL**  
that integrates start/run/stop functions with PowerDial™



**POWER RUSH™**

## DOUBLE YOUR POWER

PARALLEL KIT (#7668-0)

A Generac parallel kit allows you to double your power when pairing two inverter generators together with the same output.† Parallel kit sold separately.



\*Increases electrical current upon demand; above rated output when starting electric motors.

†Connect any two Generac 3000 or 3500 Series\* inverters for twice the power. Applies when pairing two inverter generators with the same output. Parallel kit sold separately.

# CONTROL PANEL FEATURES



## GENERATOR STATUS LIGHTS

Ready, overload and low oil

## ECONOMY MODE

Provides excellent fuel economy and noise reduction

## USB OUTLETS

Charge mobile devices including smartphones and tablets

## PARALLEL READY

Connect two inverters together for twice the power (parallel kit sold separately)

# HOW MUCH POWER DO YOU NEED?

Sizing a portable generator is easy. Check out this example:

- 1** CHOOSE WHICH DEVICES YOU WANT TO POWER AT THE SAME TIME.
- 2** RECORD THE RUNNING WATTS LISTED FOR EACH DEVICE. IF YOUR DEVICE ONLY LISTS AMPS, MULTIPLY THE AMPS BY 120V TO GET WATTAGE. EX. 15A X 120V = 1800 WATTS
- 3** ADD THE RUNNING WATTS TOGETHER FOR ALL DEVICES. THIS IS THE MINIMUM RUNNING WATTAGE REQUIREMENT FOR YOUR NEEDS.

DEVICE	RUNNING WATTS	GENERATOR SIZE
RV Air Conditioner (13,500 BTU) <sup>†</sup>	1250	Minimum running Watts for your needs ↓ <b>2300</b> RUNNING WATTS
LED/LCD Television	120	
Blue Ray Player	15	
Slow Cooker	250	
Cell Phone Charger	10	
RV Microwave	600	
<b>Total</b>	<b>2245</b>	

<sup>†</sup>Motor load, demands higher Watts at start-up.

Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

	DEVICE	RUNNING WATTS
RECREATION	RV Air Conditioner (13,500 BTU) <sup>†</sup>	1250
	Cell Phone Charger	10
	Box Fan - 20"	100
	Tablet	20
	Blue Ray Player	15
	LED/LCD Television	120
	Slow Cooker	250
	Laptop Computer	75
	Coffee Maker	900
	RV Microwave	600
JOBSITE	Blender	1000
	Hair Dryer	1500
	Lithium Ion Battery Charger	360
	Air Compressor <sup>†</sup>	1000
	Circular Saw <sup>†</sup>	1400
	Hand Drill <sup>†</sup>	600
	Belt Sander <sup>†</sup>	1200
	Reciprocating Saw <sup>†</sup>	1440
	Table Saw <sup>†</sup>	1800
	Airless Paint Sprayer	1080
HOUSEHOLD	Wet Dry Vac	900
	Quartz Halogen Work Light	1000
	Refrigerator/Freezer <sup>†</sup>	700
	Lights	600
	Desktop Computer	400
	Sump Pump <sup>†</sup>	2100
Toaster	1200	
Window AC (12,000 BTU) <sup>†</sup>	3250	

# GP3000i

## PORTABLE INVERTER GENERATOR



### SPECIFICATIONS

SERIES	GP3000i
Model #	7129
Configuration	50ST/CSA
Running Watts	2300
Starting Watts	3000
Engine Type	Generac OHV
Engine Displacement	149cc
Starting Method	Recoil Pull Start
Low Oil Shutdown	Yes
Fuel Tank Capacity (Gallons)	1.06
Run Time @ 50% Load	4.5 hrs
Run Time @ 25% Load	5.8 hrs
Rated Voltage	220 V
Low Total Harmonic Distortion (THD)	Less than 3%
Outlets	(1) 120V 20A 5-20R Duplex, (1) 120V 30A L5-30R Twist Lock, (2) USB
Parallel Ready	Yes
Handle Style	Single, Molded Into Enclosure
Dimensions (L" x W" x H")	22.2 X 13.3 X 18.4
Product Weight	59.5 lbs
Warranty - Residential	3 Year Limited
Warranty - Commercial	1 Year Limited

All portable specifications and models subject to change. Please consult factory for availability.

### PARALLEL KIT

Model # (Configuration)	7668-0
Receptacle Type	(1) 120V 50A 14-50R, (1) 120V 30A TT-30R (RV)
Covered Outlets	Yes
Rated 120 VAC Amperage	50 Amp
AC Rated Voltage	120 V
Warranty - Residential	90 Day Limited
Warranty - Commercial	90 Day Limited
Dimensions (L x W x H)	9.84" x 4.33" x 8.27"

# GENERAC®